

Capacités pour correction du facteur de puissance

Capacità per la correzione del fattore di potenza

Lampe <i>Lampada</i>			Tension <i>Tensione</i>	Capacité pour λ <i>Per la capacità λ</i> 0,90 $\pm$ 0,05	
Type <i>Tipo</i>	Puissance <i>Potenza</i>	Courant <i>Corrente</i>		50Hz $\mu F \pm 5\%$	60Hz $\mu F \pm 5\%$
Lampes à vapeur de mercure <i>Lampade a vapori di mercurio</i>	50	0,61	220/230/240	7	6
	80	0,80	220/230/240	8	7
	125	1,15	220/230/240	10	9
	250	2,13	220/230/240	18	15
	400	3,25	220/230/240	28	24
	700	5,40	220/230/240	45	40
	1000	7,50	220/230/240	60	50
Lampes à vapeur sodium haute pression <i>Lampade al sodio ad alta pressione</i>	50	0,76	220/230/240	9	7,5
	70	1	220/230/240	12	10
	100	1,20	220/230/240	13	11
	150	1,80	220/230/240	20	17
	250	3	220/230/240	32	28
	400	4,45	220/230/240	45	40
	600	6,20	220/230/240	65	55
	1000	10,30	220/230/240	100	85
Lampes aux iodures métalliques <i>Lampade ad ioduri metallici</i>	35	0,53	220/230/240	6	5
	70	1	220/230/240	12	10
	100	1,10	220/230/240	13	11
	150	1,80	220/230/240	20	17
	250	2,10	220/230/240	18	15
	250	3	220/230/240	32	28
	400	3,50	220/230/240	36	30
	1000	8,25	220/230/240	72	60
	1000	9,50	220/230/240	90	75
	2000	16,50	220/230/240	150	125
	2000	8,80	380/400/415	37	32
	2000	10,30	380/400/415	60	50
	2000	11,30	380/400/415	60	50
	2000	12,2	380/400/415	74	60

